



42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF

TECHNICAL DATA SHEET

PE15A5039

The PE15A5039 is a 25 W minimum high gain power coaxial amplifier operating in the 860 to 960 MHz frequency range. This class AB design is highly efficient with good linearity. The amplifier offers 25 Watts TYP of P1dB power, 42 dB typical small signal gain with gain flatness of ± 1.5 dB max, and an output IP3 of +58 dBm typ. The amplifier requires typically a +12V DC power supply. The connectorized SMA module is unconditionally stable and operates over the temperature range of -20°C and +65°C.

Features

- 860 to 960 MHz Frequency Range
- Psat 25 Watts typ
- Small Signal Gain: 42 dB typ
- Gain Flatness ± 1.0 dB typ
- 50 Ohms Input and Output Matched
- Unconditionally Stable
- Regulated Supply

Applications

- Military Radio
- Communication Systems
- High Gain Driver Power Amplifier
- High Gain Output Power Amplifier

Electrical Specifications (TA = +25°C, DC Voltage = 12Volts, DC Current = 6.5A)

Description	Minimum	Typical	Maximum	Units
Frequency Range	860		960	MHz
Small Signal Gain	39	42	45	dB
Gain Flatness		± 1	± 1.5	dB
Gain Variation at OTR*		± 2		dB
Output Power at 1 dB Compression Point	+43	+44		dBm
Output 3rd Intercept Point	+53	+58		dBm
Noise Figure		3.5	5	dB
Spurious			-60	dBc
Impedance (Input)		50		Ohms
Impedance (Output)		50		Ohms
Input VSWR		1.5:1	1.8:1	
Output VSWR		1.5:1	1.8:1	
Operating DC Voltage	11.5	12	13	Volts
Operating DC Current		6.5	7.5	A
Quiescent Current		2.2		A

*OTR= Base Plate Operating Temperature Range

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF PE15A5039](#)



42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF

TECHNICAL DATA SHEET

PE15A5039

Absolute Maximum Rating

Parameter	Rating	Units
Source Voltage	+13	Volts
RF input Power	+15	dBm
Maximum Load VSWR	3:1	
Operating Temperature (base-plate)	-40 to +71	°C
Storage Temperature	-55 to +125	°C



ESD Sensitive Material,
Transport material in
Approved ESD bags.
Handle only in approved
ESD Workstation.

Mechanical Specifications

Size

Length

5 in [127 mm]

Width

3 in [76.2 mm]

Height

0.85 in [21.59 mm]

Weight

0.9 lbs [408.23 g]

Input Connector

SMA Female

Output Connector

SMA Female

Cooling

HEATSINK REQUIRED use PE15C5013 or
PE15C5013F

Environmental Specifications

Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Notes:

- Values at +25 °C, sea level
- ESD Sensitive Material, Transport material in Approved ESD bags. Handle only in approved ESD Workstation.
- Heat Sink Required for Proper Operation, Unit is cooled by conduction to heat sink.



Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF PE15A5039](#)



42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power
Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF

TECHNICAL DATA SHEET

PE15A5039

Amplifier Power-up Precautions

- 1.) Confirm that proper ESD precautions and controls are always in place before handling any Amplifier module.
- 2.) Confirm adequate thermal management is in place to effectively dissipate heat away from the Amplifier package. The Amplifier operational baseplate temperature must be within the operational temperature range stated in the Amplifier datasheet. Depending on the design and thermal requirements, using a heatsink with cooling fan is always recommended for safe reliable operation. A heat sink without a cooling fan may also be used. Damage caused from overheating will void the warranty.
- 3.) Confirm adequate system grounding is established. The DC power supply and Amplifier must have a common ground in order to operate properly.
- 4.) Power Amplifiers may require additional DC Current when initially powered-up. Depending on the design, the input current draw could range from an additional 10% to 100% above the maximum rated DC current of the Amplifier. This varies based on product part number.
- 5.) Confirm the DC power supply, if limited, is set to allow for additional start-up current that's rated for the Power Amplifier.
- 6.) Confirm the system is designed and calibrated for 50 ohms. Any impedance mismatch may cause performance issues.
- 7.) Perform a CALIBRATION (if required) with the loads before connecting the Amplifier to the Network Analyzer to ensure proper performance.
- 8.) Use a fixed attenuator between the signal source and input port of the Amplifier to optimize the input VSWR match.
- 9.) Confirm the input power level at the input port of the amplifier does not exceed the maximum rated limit for input power (as stated in the Amplifier datasheet).
 P_{in} for Small Signal Gain = P1dB-SSG-10 dB
 P_{in} for P1dB = P1dB-SSG+1 dB
- 10.) Confirm the Network Analyzer is always connected to the Amplifier first before DC power is applied to the Amplifier.
- 11.) As long as the input and output ports of the amplifier are connected to a 50Ohm load and RF signal power is applied, the Amplifier can be powered up with DC voltage.
- 12.) Confirm the Amplifier output load is matched for a 50 Ohm impedance and will not exceed the maximum rated VSWR or Return Loss limit for the Amplifier. Exceeding the maximum rated VSWR or Return Loss limit will result in reflected signal power that could damage the Amplifier and void the warranty.
- 13.) **Power Amplifier connected to an Antenna for signal transmission** - It's strongly recommended to use a high power fixed attenuator pad or an Isolator between the output port of the Amplifier and input port to the antenna. Any reflected signal power due to impedance mismatch will likely damage the Amplifier and void the warranty.
- 14.) The attenuator or isolator used at the output port of the Amplifier must be rated to handle the output power level and operational frequency band of the amplifier.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF PE15A5039](#)




42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power
Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF

TECHNICAL DATA SHEET

PE15A5039

Typical Performance Data



42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.


Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF PE15A5039](https://www.pasternack.com/42-db-gain-960-mhz-high-power-high-gain-amplifier-ip3-sma-pe15a5039-p.aspx)

URL: <https://www.pasternack.com/42-db-gain-960-mhz-high-power-high-gain-amplifier-ip3-sma-pe15a5039-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE15A5039 CAD Drawing

42 dB Gain, 25 Watt P1dB, 860 MHz to 960 MHz, High Power
Amplifier, SMA Input, SMA Output, 58 dBm IP3, 3.5 dB NF



NOTE:
HEAT SINK REQUIRED FOR PROPER OPERATION,
UNIT IS COOLED BY CONDUCTING TO HEAT SINK.

PE PASTERNAK
THE ENGINEER'S RF SOURCE

Pasternack Enterprises, Inc.
P.O. Box 16759 | Irvine | CA | 92623
Phone: (949) 261-1920 | Fax: (949) 261-7451
Website: www.pasternack.com | E-Mail: sales@pasternack.com

DWG TITLE

PE15A5039

NOTES:
1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].

FSCM NO. 53919

CAD FILE 071315

SCALE N/A

SIZE A

2233