

Broadsens ultra-low power wireless vibration sensors can be mounted with magnet base, mounting pads, mounting studs, or epoxy in tight spaces. Magnet mount is the easiest way to fix the sensor to a ferromagnetic structure such as iron, cobalt, nickel and their alloys. SVT200-A, SVT300-A and SVT400-A wireless vibration sensors can be screwed into the magnet base and attached to metal structures for quick vibration monitoring. The bottom of the magnet mount has H-shape legs, which makes it applicable to both flat and curved structures, even for small pipes. Mount pads and epoxy mounting provide better frequency response up to 10kHz. Stud mount is the most reliable method for long-term online monitoring with the maximum frequency response, but drilling hole is required.



Wireless vibration & temperature sensor with magnet base mounted on curved structure

| Accessories description | Magnet base | Mounting pad | Mounting stud |
|-----------------------------|---|---|--|
| SKU | ACE-MAG-02 | ACE-PAD-02 | ACE-STUD-01 |
| Pictures |  |  |  |
| Size | Height: 23mm (0.75 inch) including H-shape legs; diameter: 29mm (1.18 inch); screw thread: M6, 1mm thread | Width: 30mm (1.18 inch), height: 11mm (0.43 inch); screw thread: M8 (use with ACE-STUD-01 mounting stud together) | Bottom: M8x10L (Length: 10mm (0.39 inch), 1.25mm thread); top: M6*6L (Length: 6mm (0.24 inch), 1mm thread) |
| Weight | 77g (2.2oz) | 58g (2.0oz) | 5g (0.1oz) |
| Materials | Stainless steel | Stainless steel | Stainless steel |
| Recommended frequency range | DC up to 5kHz | DC up to 10kHz | No limit |
| Installation illustration |  |  |  |

“Broadsens, sense the broader world”

Website: www.broadsens.com
 Sales: sales@broadsens.com
 Support: support@broadsens.com

USA Headquarter
 . 100 S Murphy Ave Ste 200, Sunnyvale, CA, 94086
Distributors
[Contact Broadsens](#)