

# 3 dB Fixed Attenuator, 75 Ohm F Male to 75 Ohm F Female Brass Nickel Body Rated to 2 Watts Up to 1,000 MHz



# **RF Fixed Attenuators Technical Data Sheet**

PE7057-3

### **Features**

- Bidirectional
- DC to 1 GHz Frequency Range
- Attenuation 3±0.5 dB

- Max Power 2 Watts (CW)
- VSWR < 1.3:1</li>

# **Applications**

- Instrumentation
- Precision measurements
- Prototyping and characterization
- · Production systems

### Description

Pasternack carries a wide range of fixed attenuators with a broad selection of attenuation levels, frequency ranges, and power dissipation ranges. RF microwave attenuators (also known as RF pads) lower the amplitude of a signal (attenuate) a known amount and can be used in a wide variety of applications. These attenuator pads are used when a signal needs to be reduced to protect measurement equipment or other circuitry, to extend the range of power meters and amplifiers, and to impedance match circuits by reducing the VSWR seen by adjacent components. RF attenuators can prevent signal overload in amplifiers, receivers and detectors, adjusting the signal level to a range that is optimal.

Few RF components are as commonly used as fixed coaxial attenuators, and Pasternack carries one of the largest in-stock varieties and ships them same day. The 3 dB Fixed Attenuator PE7057-3 is rated to 2 Watts and operates from DC to 1,000 MHz. The versatile coaxial package uses F male to F female connectors and is also REACH and RoHS compliant.

### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		1,000	MHz
Impedance		75		Ohms
Nominal Attenuation		3		dB
Attenuation Accuracy		±0.5		dB
VSWR			1.3:1	
Input Power, CW			2	Watts

### **Mechanical Specifications**

Size

 Length
 1.47 in [37.34 mm]

 Width/Diameter
 0.44 in [11.18 mm]

 Weight
 0.034 lbs [15.42 g]

 Body Material and Plating
 Brass, Nickel

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 3 dB Fixed Attenuator, 75 Ohm F Male to 75 Ohm F Female Brass Nickel Body Rated to 2 Watts Up to 1,000 MHz PE7057-3

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



# 3 dB Fixed Attenuator, 75 Ohm F Male to 75 Ohm F Female Brass Nickel Body Rated to 2 Watts Up to 1,000 MHz



## **RF Fixed Attenuators Technical Data Sheet**

PE7057-3

Configuration

Design Package Style Fixed, Bidirectional Connectorized Module

#### Connectors

Description	Connector 1	Connector 2
Туре	F Male	F Female
Hex Size	7/16 in.	
Torque	15 in-lbs 1.7 Nm	

### **Environmental Specifications**

Compliance Certifications (visit www.Pasternack.com for current document)

RoHS Compliant REACH Compliant

12/17/2015

#### **Plotted and Other Data**

Notes:

3 dB Fixed Attenuator, 75 Ohm F Male to 75 Ohm F Female Brass Nickel Body Rated to 2 Watts Up to 1,000 MHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 3 dB Fixed Attenuator, 75 Ohm F Male to 75 Ohm F Female Brass Nickel Body Rated to 2 Watts Up to 1,000 MHz PE7057-3

URL: http://www.pasternack.com/3db-fixed-f-male-f-female-2-watts-attenuator-pe7057-3-p.aspx

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

# PE7057-3 CAD Drawing

3 dB Fixed Attenuator, 75 Ohm F Male to 75 Ohm F Female Brass Nickel Body Rated to 2 Watts Up to 1,000 MHz

