

Low PIM 4 Hole Flange Mount N Female to QMA Female Adapter



PE91710

Configuration

- N Female Connector 1
- QMA Female Connector 2
- 50 Ohm
- Low PIM Design
- Straight Body Geometry
- 4 Hole Flange Mount Method

Features

- Typical PIM levels of -155 dBc
- 200 μ in contact plating
- Silver Plated Beryllium Copper Contact
- Max of VSWR 1.15:1 at 3GHz, Max of VSWR 1.2:1 at 6GHz

Applications

- Allows Connection Between Series
- General Purpose Test
- Rack Mounted Equipment
- Low PIM Applications

Description

Pasternack's PE91710 4 hole flange type N female to QMA female adapter is part of our full line of RF components available for same-day shipping. Our type N to QMA adapter has a female to female gender configuration in a low PIM design. PE91710 type N female to QMA female adapter operates to 6 GHz. The Pasternack adapter provides a passive intermodulation of -155 dBc typical. This RF type N 4 hole flange to QMA adapter allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		6	GHz
Impedance		50 Ohm		
Passive Intermodulation		-155		dBc
Dielectric Withstanding Voltage (AC)			1,000	Vrms

Mechanical Specifications

Size	
Length	1.12 in [28.45 mm]
Width	1.00 in [25.40 mm]
Height	1.00 in [25.40 mm]
Weight	0.06 lbs [29.03 g]

Description	Connector 1	Connector 2
Type	N Female	QMA Female
Polarity	Standard	Standard

Low PIM 4 Hole Flange Mount N Female to QMA Female Adapter



PE91710

Material Specifications

Description	Connector 1		Connector 2	
	Material	Plating	Material	Plating
Type	N Female		QMA Female	
Contact	Beryllium Copper	Silver 200μ in	Beryllium Copper	Silver 200μ in
Insulation	PTFE		PTFE	
Outer Conductor	Brass	Tri-Metal	Brass	Tri-Metal
Body	Brass	Tri-Metal	Brass	Tri-Metal

Environmental Specifications

Temperature

Operating Range -40 to +155 °C

Environmental Specification Notes:
IEC 61169-16

Compliance Certifications (see [product page](#) for current document)

Plotted and Other Data

Low PIM 4 Hole Flange Mount N Female to QMA Female Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [Low PIM 4 Hole Flange Mount N Female to QMA Female Adapter PE91710](#)

URL: <https://www.pasternack.com/low-pim-4-hole-flange-mount-n-female-to-qma-female-adapter-pe91710-p.aspx>

The information contained within this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part in order to implement improvements. Pasternack Enterprises reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack Enterprises does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack Enterprises does not assume liability arising out of the use of any part or document.

PE91710 CAD Drawing

Low PIM 4 Hole Flange Mount N Female to QMA Female Adapter

