SIEMENS

Data sheet

3RT1054-6AM36



power contactor, AC-3e/AC-3 115 A, 55 kW / 400 V, AC (50-60 Hz) / DC Uc: 200-220 V 3-pole, auxiliary contacts 2 NO + 2 NC drive: conventional main circuit: busbar control and auxiliary circuit: screw terminal

product brand name	SIRIUS
product brand name	
product designation	Power contactor 3RT1
product type designation	JRT I
General technical data	
size of contactor	S6
product extension	
function module for communication	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
 at AC in hot operating state 	21 W
 at AC in hot operating state per pole 	7 W
without load current share typical	5.2 W
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	1 000 V
 of auxiliary circuit with degree of pollution 3 rated value 	500 V
surge voltage resistance	
 of main circuit rated value 	8 kV
 of auxiliary circuit rated value 	6 kV
maximum permissible voltage for protective separation between coil and main contacts according to EN 60947-1	690 V
shock resistance at rectangular impulse	
• at AC	8,5g / 5 ms, 4,2g / 10 ms
• at DC	8,5g / 5 ms, 4,2g / 10 ms
shock resistance with sine pulse	
• at AC	13,4g / 5 ms, 6,5g / 10 ms
• at DC	13,4g / 5 ms, 6,5g / 10 ms
mechanical service life (operating cycles)	
 of contactor typical 	10 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
of the contactor with added auxiliary switch block typical	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	05/01/2012
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
during operation	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %

Main circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
 at AC-3 rated value maximum 	1 000 V
 at AC-3e rated value maximum 	1 000 V
operational current	
 at AC-1 at 400 V at ambient temperature 40 °C rated value 	160 A
• at AC-1	
— up to 690 V at ambient temperature 40 °C rated value	160 A
— up to 690 V at ambient temperature 60 °C rated value	140 A
 — up to 1000 V at ambient temperature 40 °C rated value 	80 A
— up to 1000 V at ambient temperature 60 °C rated value	80 A
• at AC-3	
— at 400 V rated value	115 A
— at 500 V rated value	115 A
— at 690 V rated value	115 A
— at 1000 V rated value	53 A
• at AC-3e	
— at 400 V rated value	115 A
— at 500 V rated value	115 A
— at 690 V rated value	115 A
— at 1000 V rated value	53 A
 at AC-4 at 400 V rated value 	97 A
 at AC-5a up to 690 V rated value 	140 A
 at AC-5b up to 400 V rated value at AC-6a 	95 A
 — up to 230 V for current peak value n=20 rated value 	115 A
 — up to 400 V for current peak value n=20 rated value 	115 A
 — up to 500 V for current peak value n=20 rated value 	115 A
 — up to 690 V for current peak value n=20 rated value 	115 A
 — up to 1000 V for current peak value n=20 rated value 	53 A
• at AC-6a	
 — up to 230 V for current peak value n=30 rated value 	98 A
 — up to 400 V for current peak value n=30 rated value 	98 A
— up to 500 V for current peak value n=30 rated value	98 A
— up to 690 V for current peak value n=30 rated value	98 A
 — up to 1000 V for current peak value n=30 rated value 	53 A
minimum cross-section in main circuit at maximum AC-1 rated value	70 mm²
operational current for approx. 200000 operating cycles at AC-4	
at 400 V rated value	54 A
at 690 V rated value	48 A
operational current	
at 1 current path at DC-1	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	18 A
— at 220 V rated value	3.4 A
— at 440 V rated value	0.8 A
— at 600 V rated value	0.5 A
with 2 current paths in series at DC-1	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A

— at 220 V rated value	20 A
— at 440 V rated value	3.2 A
— at 600 V rated value	1.6 A
 with 3 current paths in series at DC-1 	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A
— at 220 V rated value	160 A
— at 440 V rated value	11.5 A
— at 600 V rated value	4 A
 at 1 current path at DC-3 at DC-5 	
— at 24 V rated value	160 A
— at 60 V rated value	7.5 A
— at 220 V rated value	0.6 A
— at 440 V rated value	0.17 A
— at 600 V rated value	0.12 A
 with 2 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A
— at 220 V rated value	2.5 A
— at 440 V rated value	0.65 A
— at 600 V rated value	0.37 A
 with 3 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A
— at 220 V rated value	160 A
— at 440 V rated value	1.4 A
— at 600 V rated value	0.75 A
operating power	
• at AC-3	
— at 230 V rated value	37 kW
— at 400 V rated value	55 kW
— at 500 V rated value	75 kW
— at 690 V rated value	110 kW
— at 1000 V rated value	75 kW
• at AC-3e	
— at 230 V rated value	37 kW
— at 400 V rated value	55 kW
— at 500 V rated value	75 kW
— at 690 V rated value	110 kW
— at 1000 V rated value	75 kW
operating power for approx. 200000 operating cycles at AC- 4	
 at 400 V rated value 	29 kW
at 690 V rated value	48 kW
operating apparent power at AC-6a	
up to 230 V for current peak value n=20 rated value	40 000 kVA
• up to 400 V for current peak value n=20 rated value	80 000 VA
• up to 500 V for current peak value n=20 rated value	100 000 VA
• up to 690 V for current peak value n=20 rated value	130 000 VA
• up to 1000 V for current peak value n=20 rated value	90 000 VA
operating apparent power at AC-6a	
• up to 230 V for current peak value n=30 rated value	30 000 VA
 up to 400 V for current peak value n=30 rated value 	60 000 VA
 up to 500 V for current peak value n=30 rated value 	80 000 VA
 up to 690 V for current peak value n=30 rated value 	110 000 VA
• up to 1000 V for current peak value n=30 rated value	90 000 VA
short-time withstand current in cold operating state up to	
40 °C	

 limited to 1 s switching at zero current maximum 	2 565 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 5 s switching at zero current maximum 	1 654 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 10 s switching at zero current maximum 	1 170 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 30 s switching at zero current maximum 	729 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 60 s switching at zero current maximum 	572 A; Use minimum cross-section acc. to AC-1 rated value
no-load switching frequency	
• at AC	2 000 1/h
• at DC	2 000 1/h
operating frequency	
● at AC-1 maximum	800 1/h
• at AC-2 maximum	400 1/h
 at AC-3 maximum 	1 000 1/h
 at AC-3e maximum 	1 000 1/h
• at AC-4 maximum	130 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	AC/DC
control supply voltage at AC	
● at 50 Hz rated value	200 220 V
● at 60 Hz rated value	200 220 V
control supply voltage at DC	
rated value	200 220 V
operating range factor control supply voltage rated value of magnet coil at DC	
• initial value	0.8
full-scale value	1.1
operating range factor control supply voltage rated value of magnet coil at AC	
• at 50 Hz	0.8 1.1
• at 60 Hz	0.8 1.1
design of the surge suppressor	with varistor
apparent pick-up power of magnet coil at AC	
• at 50 Hz	300 VA
• at 60 Hz	300 VA
inductive power factor with closing power of the coil	0.0
• at 50 Hz	0.9
• at 60 Hz	0.9
apparent holding power of magnet coil at AC	5.0.1/4
● at 50 Hz ● at 60 Hz	5.8 VA
	5.8 VA
inductive power factor with the holding power of the coil	0.9
● at 50 Hz ● at 60 Hz	0.8 0.8
closing power of magnet coil at DC	360 W
holding power of magnet coil at DC	5.2 W
closing delay	
• at AC	20 95 ms
• at DC	20 95 ms
opening delay	
• at AC	40 60 ms
• at DC	40 60 ms
arcing time	10 15 ms
control version of the switch operating mechanism	Standard A1 - A2
Auxiliary circuit	
number of NC contacts for auxiliary contacts instantaneous contact	2
number of NO contacts for auxiliary contacts instantaneous contact	2
operational current at AC-12 maximum	10 A
operational current at AC-15	
• at 230 V rated value	6 A
• at 400 V rated value	3 A
• at 500 V rated value	2 A

at 690 V rated value	1 A
operational current at DC-12	
at 24 V rated value	10 A
• at 48 V rated value	6 A
• at 60 V rated value	6 A
 at 110 V rated value 	3 A
 at 125 V rated value 	2 A
 at 220 V rated value 	1 A
• at 600 V rated value	0.15 A
operational current at DC-13	
 at 24 V rated value 	10 A
 at 48 V rated value 	2 A
• at 60 V rated value	2 A
• at 110 V rated value	1 A
• at 125 V rated value	0.9 A
at 220 V rated value	0.3 A
• at 600 V rated value	0.1 A
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	124 A
• at 600 V rated value	125 A
yielded mechanical performance [hp]	
• for single-phase AC motor	
— at 230 V rated value	25 hp
• for 3-phase AC motor	
— at 200/208 V rated value	40 hp
— at 220/230 V rated value	50 hp
— at 460/480 V rated value	100 hp
— at 575/600 V rated value	125 hp
contact rating of auxiliary contacts according to UL	A600 / Q600
Short-circuit protection	
Short-circuit protection design of the fuse link	
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit	
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required	gG: 355 A (690 V, 100 kA)
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA)
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA)
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA)
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/mounting/dimensions mounting position fastening method • side-by-side mounting	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit — with type of coordination 1 required — with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - downwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm 10 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - downwards - at the side	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - downwards - at the side • for grounded parts	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 0 mm 0 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - forwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 0 mm 20 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - upwards - upwards - upwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm 20 mm 10 mm 10 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - upwards - at the side	gG: 355 A (690 V, 100 kA), gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - forwards - upwards - at the side - downwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 0 mm 20 mm 10 mm 0 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - forwards - at the side - downwards - at the side - forwards - upwards - forwards - forwar	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 10 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - downwards - at the side • for grounded parts - at the side - downwards - at the side - forwards - for live parts - forwards	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm 10 mm 10 mm 20 mm 20 mm
Short-circuit protection design of the fuse link • for short-circuit protection of the main circuit - with type of coordination 1 required - with type of assignment 2 required • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method • side-by-side mounting height width depth required spacing • with side-by-side mounting - forwards - upwards - at the side • for grounded parts - forwards - at the side - downwards - at the side - forwards - upwards - forwards - forwar	gG: 355 A (690 V, 100 kA) gG: 250 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 250 A (415 V, 50 kA) gG: 10 A (500 V, 1 kA) with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back screw fixing Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 10 mm

— at the side			10 mm		
onnections/ Terminals	;				
type of electrical conr	nection				
 for main current 	circuit		Connection bar		
 for auxiliary and 	control circuit		screw-type terminals		
 at contactor for a 	uxiliary contacts		Screw-type terminals		
 of magnet coil 			Screw-type terminals		
width of connection b	ar		17 mm		
thickness of connecti	on bar		3 mm		
diameter of holes			9 mm		
number of holes			1		
connectable conducto	or cross-section for main	contacts			
 stranded 			25 120 mm²		
	or cross-section for auxil				
 solid or stranded 			0.5 4 mm²		
	ith core end processing		0.5 2.5 mm ²		
	onductor cross-sections		0.0 2.0 mm		
 for auxiliary containing 					
	acis		$2x (0 = 1 = mm^2) 2x (0 = 7)$	$5 - 2 E mm^2$ may $2 \times (0.7E)$	(1 mm^2)
— solid	and and		· · · · ·	5 2.5 mm ²), max. 2x (0.75	<i>'</i>
— solid or stra				5 2,5 mm²), max. 2x (0,75	4 mm²)
2	ded with core end processi	0	2x (0.5 1.5 mm²), 2x (0.7		
 for AWG cables 	for auxiliary contacts		2x (20 16), 2x (18 14),	1x 12	
AWG number as code section	d connectable conductor	r cross			
	acte		18 14		
 for auxiliary contract data 	auis	_	18 14		
afety related data					_
product function					
 mirror contact ac 	cording to IEC 60947-4-1		Yes		
 positively driven 	operation according to IEC	60947-5-1	No		
B10 value with high der	mand rate according to SN	31920	1 000 000		
	nterval or service life accor	rding to IEC	20 a		
61508					
protection class IP on	the front according to IE	EC 60529	IP00; IP20 with box termina	l/cover	
touch protection on th	ne front according to IEC	60529	finger-safe, for vertical conta	act from the front with box ter	rminal/cover
suitability for use					
 safety-related sw 	ritching OFF		Yes		
ertificates/ approvals					
General Product App	roval				
(SP)	<u>Confirmation</u>			KC	EAC
EMC	Functional Safety/Safety of Ma- chinery	Declaration of Co	onformity	Test Certificates	
RCM	<u>Type Examination Cer-</u> <u>tificate</u>	CE EG-Konf.	UK CA	Special Test Certific- ate	<u>Type Test Certific-</u> ates/Test Report
Marine / Shipping					other
ABS	Lloyd's Register us	PRS	RMRS	DINV-GL	<u>Miscellaneous</u>

_

7/10/2023

Subject to change without notice © Copyright Siemens

Confirmation	0 0		
	Conti	rmat	ion

Miscellaneous

Confirmation

Special Test Certificate

Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...) https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT1054-6AM36

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT1054-6AM36

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT1054-6AM36

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT1054-6AM36&lang=en

Characteristic: Tripping characteristics, I²t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RT1054-6AM36/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT1054-6AM36&objecttype=14&gridview=view1









last modified:

2/10/2023 🖸