

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

Please be informed that the data shown in this PDF document is generated from our online catalog. Please find the complete data in the user documentation. Our general terms of use for downloads are valid.



Multi-functional energy measuring device without display with 24 V DC supply and integrated Modbus/TCP interface for measuring electrical parameters in low-voltage installations up to 690 V ([phoenixcontact.com/empro-help](https://www.phoenixcontact.com/empro-help))

## Commercial data

Item number	1127061
Packing unit	1 pc
Minimum order quantity	1 pc
Sales key	C446
Product key	CK4C21
GTIN	4063151055332
Weight per piece (including packing)	385 g
Weight per piece (excluding packing)	370 g
Customs tariff number	90303100
Country of origin	DE

## Technical data

### Product properties

Product type	Energy measuring device
Product family	EMpro

### Electrical properties

Maximum power dissipation for nominal condition	10 VA
Mains type	3-phase (3 or 4-conductor), 2-phase (2-conductor), and single-phase (1-conductor)

#### Electrical isolation

Test voltage	4 kV AC (50 Hz, 60 s)
Pollution degree	2

#### Electrical isolation Housing against all potentials IEC 61010-1

Standards/regulations	IEC 61010-1
Overvoltage category	III (300 V AC) II (600 V AC)
Insulation	Reinforced insulation

#### Electrical isolation Supply voltage

Insulation	Functional insulation
------------	-----------------------

#### Electrical isolation Voltage measurement input against all other potentials IEC 61010-1

Standards/regulations	IEC 61010-1
Measuring category	III (300 V AC) II (600 V AC)
Insulation	Reinforced insulation

#### Electrical isolation Current measurement input against all other potentials

Insulation	Functional insulation
------------	-----------------------

#### Electrical isolation Digital I/Os

Insulation	Functional insulation
------------	-----------------------

#### Electrical isolation Communication interface

Insulation	Functional insulation
------------	-----------------------

#### Supply

Supply voltage	24 V DC $\pm$ 25 %
Supply voltage range	18 V DC ... 30 V DC
Power consumption	< 4 W

## Input data

### General

Measuring principle	True r.m.s. value measurement
---------------------	-------------------------------

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

Measured value	AC sine (50 Hz/60 Hz)
Acquisition of harmonics	up to 63rd harmonic
Description of the input	Digital input in accordance with IEC/EN 61131-2 (type 3)
Number	1
Voltage input signal	24 V DC 0 V DC ... 30 V DC
Current input signal	2 mA ... 15 mA
Protection	250 mA (fast-blow)

## Measurement: Voltage

Input name	Voltage measuring input V1, V2, V3
Input voltage range direct	35 V AC ... 690 V AC (Phase/Phase) 20 V AC ... 400 V AC (Phase/neutral conductor)
Input voltage range via external transformers	60 V AC ... 2000000 V AC (primary) 60 V AC ... 400 V AC (secondary)
Surge voltage capacity	760 V AC (Phase/Phase)
Precision	0.2 %
Power consumption	< 2 VA

## Measurement: Current

Input name	Current measurement I1, I2, I3
Input current	1 A (secondary) 5 A (secondary)
Measuring range	1 A ... 20000 A (primary)
Overload capacity	6 A ( $I_{max}$ )
Response threshold from measuring range nominal value	10 mA (1 A) 50 mA (5 A)
Precision	0.2 %
Current overload	50 A for 1 s
Power consumption	< 0.5 VA

## Measurement: Power

Precision	0.5 %
Active energy (IEC 62053-22)	Class 0.5 S
Reactive power (IEC 62053-23)	Class 2
ANSI C12.20	Class 0.5 S

## Output data

Output description	Digital output in accordance with IEC/EN 61131-2 (type 3)
Number	1
Current output signal	$\leq 100$ mA
Voltage output signal	24 V DC
Protection	250 mA (fast-blow)

## Connection data

1127061

<https://www.phoenixcontact.com/us/products/1127061>

## Current / voltage / supply

Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section rigid	0.2 mm <sup>2</sup> ... 6 mm <sup>2</sup>
Conductor cross section flexible	0.2 mm <sup>2</sup> ... 4 mm <sup>2</sup>
Conductor cross section AWG	24 ... 10
Tightening torque	0.5 Nm ... 0.6 Nm

## Digital I/O / communication

Connection method	Screw connection
Stripping length	7 mm
Screw thread	M3
Conductor cross section rigid	0.14 mm <sup>2</sup> ... 2.5 mm <sup>2</sup>
Conductor cross section flexible	0.14 mm <sup>2</sup> ... 1.5 mm <sup>2</sup>
Conductor cross section AWG	26 ... 14
Tightening torque	0.5 Nm ... 0.6 Nm

## Interfaces

### Data: Network interface

Communication protocol	Modbus/TCP
	REST
Connection method	RJ45

## Dimensions

Width	90 mm
Height	80 mm
Depth	64 mm

## Material specifications

Color	gray (RAL 7042)
-------	-----------------

## Environmental and real-life conditions

### Ambient conditions

Degree of protection (Housing)	IP20 (Housing)
Ambient temperature (operation)	-25 °C ... 70 °C
Ambient temperature (storage/transport)	-30 °C ... 80 °C
Altitude	≤ 2000 m
Max. permissible relative humidity (operation)	≤ 95 % (non-condensing)

## Approvals

### CE

Certificate	CE-compliant
-------------	--------------

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## UKCA

Certificate	UKCA-compliant
-------------	----------------

## UL, USA/Canada

Identification	UL/C-UL Listed UL 61010-1
----------------	---------------------------

## UL data

Operating mode	Indoor use
----------------	------------

## UL data

Operating mode	Indoor use
----------------	------------

## Mounting

Mounting type	DIN rail mounting
Mounting position	Horizontal DIN rail

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## Approvals

To download certificates, visit the product detail page: <https://www.phoenixcontact.com/us/products/1127061>



**UL Listed**

Approval ID: FILE E 357804



**cUL Listed**

Approval ID: FILE E 357804

**cULus Listed**

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## Classifications

### ECLASS

ECLASS-11.0	27142330
ECLASS-12.0	27142330
ECLASS-13.0	27142330

### ETIM

ETIM 9.0	EC002301
----------	----------

### UNSPSC

UNSPSC 21.0	41113600
-------------	----------

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## Environmental product compliance

### EU RoHS

Fulfills EU RoHS substance requirements	Yes
Exemption	7(a), 7(c)-I

### China RoHS

Environment friendly use period (EFUP)	EFUP-50
	An article-related China RoHS declaration table can be found in the download area for the respective article under "Manufacturer declaration". For all articles with EFUP-E, no China RoHS declaration table issued and required.

### EU REACH SVHC

REACH candidate substance (CAS No.)	Lead(CAS: 7439-92-1)
SCIP	5743539f-b522-4920-8fbe-11481411b979



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## Accessories

### PACT MCR-V1-21-44 - Current transformer

2277268

<https://www.phoenixcontact.com/us/products/2277268>



Bus-bar current transformer, primary current can be selected between 50...500 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

---

### PACT MCR-V2- 3015- 60 - Current transformer

2277271

<https://www.phoenixcontact.com/us/products/2277271>



Window-type current transformer, primary current can be selected between 50...750 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## PACT MCR-V2-3015-60-PT - Current transformer

2907413

<https://www.phoenixcontact.com/us/products/2907413>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (50 ... 750) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

---

## PACT MCR-V2- 4012- 70 - Current transformer

2277284

<https://www.phoenixcontact.com/us/products/2277284>



Window-type current transformer, primary current can be selected between 75... 1000 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

# EEM-MB370-24DC - Measuring instrument

1127061

<https://www.phoenixcontact.com/us/products/1127061>

## PACT MCR-V2-4012-70-PT - Current transformer

2907414

<https://www.phoenixcontact.com/us/products/2907414>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (100 ... 1000) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

---

## PACT MCR-V2- 5012- 85 - Current transformer

2277297

<https://www.phoenixcontact.com/us/products/2277297>



Window-type current transformer, primary current can be selected between 100..1500 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

# EEM-MB370-24DC - Measuring instrument



1127061

<https://www.phoenixcontact.com/us/products/1127061>

## PACT MCR-V2-5012-85-PT - Current transformer

2907416

<https://www.phoenixcontact.com/us/products/2907416>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (100 ... 1500) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

---

## PACT MCR-V2- 6015- 85 - Current transformer

2277336

<https://www.phoenixcontact.com/us/products/2277336>



Window-type current transformer, primary current can be selected between 200 . . . 1,250 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

# EEM-MB370-24DC - Measuring instrument

1127061

<https://www.phoenixcontact.com/us/products/1127061>



## PACT MCR-V2-6015-85-PT - Current transformer

2907417

<https://www.phoenixcontact.com/us/products/2907417>



Window-type current transformer with screw and Push-in connection technology, conductor connection for Push-in: from directly above, no tools required. The following can be selected: primary current (200 ... 1600) A AC, secondary current (1 or 5) A AC, accuracy class 0.5 or 1, VA power

---

## PACT MCR-V2-10020-129 - Current transformer

2277378

<https://www.phoenixcontact.com/us/products/2277378>



Window-type current transformer, primary current can be selected between 800 and 4,000 A AC, secondary current can be selected 1 A AC or 5 A AC, accuracy class can be selected 0.5 or 1, rated power can be selected

# EEM-MB370-24DC - Measuring instrument

1127061

<https://www.phoenixcontact.com/us/products/1127061>



## PACT MCR-V3-60 - Current transformer

2277417

<https://www.phoenixcontact.com/us/products/2277417>



Winding current transformer, primary current can be selected between 1...40 A AC; secondary current can be selected as 1 A AC or 5 A AC; accuracy class can be selected as 0.5 or 1; rated power can be selected

---

Phoenix Contact 2024 © - all rights reserved

<https://www.phoenixcontact.com>

Phoenix Contact USA  
586 Fulling Mill Road  
Middletown, PA 17057, United States  
(+717) 944-1300  
[info@phoenixcon.com](mailto:info@phoenixcon.com)