

DC Block on Inner and Outer Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz



DC Blocks Technical Data Sheet

PE8239

Features

- Inner/Outer DC Block
- Operates from 100 MHz to 50 GHz

Applications

- Test & Measurement
- Ground Loop Elimination
- Signal to Noise Ratio (SNR) Improvement

Good Insertion Loss of 1.5 dB Max

Description

Pasternack's PE8239 is an inner and outer DC block with 2.4 mm connectors. It has a blocking capacitor on the inner and outer conductor and operates from 100 MHz to 50 GHz. Our BNC DC block offers good insertion loss of 1.5 dB and has a maximum operating voltage of 75 Vdc. DC blocks are commonly used to filter out unwanted DC signals, while allowing AC drive signals to pass through. They can help improve signal to noise ratio (SNR), eliminate ground loops, or provide isolation in your test setup. All of Pasternack's DC blocks are in stock and available to ship same-day.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	0.1		50	GHz
Impedance		50		Ohms
VSWR			1.75:1	
Insertion Loss			1.5	dB
Operating Voltage (DC)			75	Volts

Mechanical Specifications

Size Length Width	1.125 in [28.58 mm] 0.5 in [12.7 mm]	
Weight	0.016 lbs [7.26 g]	
Housing Material and Plating	Plastic	
Configuration Design Package Type	Inner/Outer DC Block Connectorized	

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: DC Block on Inner and Outer Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz PE8239

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



DC Block on Inner and Outer Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz



PE8239

DC Blocks Technical Data Sheet

Description **Connector 1 Connector 2** 2.4mm Male 2.4mm Female Туре Inner Conductor Material and Plating Beryllium Copper, Gold Beryllium Copper, Gold Coupling Nut Material and Plating Stainless Steel, Gold Hex Size 5/16 inch Stainless Steel, Gold Body Material and Plating Stainless Steel, Gold **Environmental Specifications** Temperature **Operating Range** +5 to +75 deg C Compliance Certifications (see product page for current document) Plotted and Other Data Notes: DC Block on Inner and Outer Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: DC Block on Inner and Outer Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz PE8239

URL: https://www.pasternack.com/50-ohm-dc-block-24mm-male-to-24mm-female-mhz-50-ghz-pe8239-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE8239 CAD Drawing DC Block on Inner and Outer Conductor 2.4mm Male to 2.4mm Female Operating From 100 MHz to 50 GHz

