SIEMENS

Data sheet

3RT2926-5AT61



magnetic coil 600 V AC, 60 Hz, for contactors 3RT2325-.A, 3RT2.26-.A, 3RT2.27-.A and 3RT2028-.A

	10°			
product brand name		SIRIUS		
product designation		Magnet coil		
eneral technical data				
power loss [V·A] of magnet coil at AC typical		9.8 VA		
Substance Prohibitance (Date)		10/01/2009		
type of voltage of the control supply voltage		AC		
control supply voltage 1 at AC				
• at 50 Hz rated value		660 V		
operating range factor control suppl magnet coil at AC	y voltage rated value of			
• at 50 Hz		0.8 1.1		
• at 60 Hz		0.85 1.1		
apparent pick-up power of magnet c	oil at AC			
• at 50 Hz		77 VA		
• at 60 Hz		87 VA		
inductive power factor with closing	power of the coil			
• at 50 Hz		0.82		
• at 60 Hz		0.76		
apparent holding power of magnet c	oil at AC			
• at 50 Hz		9.8 VA		
• at 60 Hz		87 VA		
inductive power factor with the hold	ing power of the coil			
• at 50 Hz		0.25		
• at 60 Hz		0.8		
pprovals Certificates				
General Product Approval	EMC	Declaration of Confo	rmity	Marine / Shipping
General Product Approval Confirmation		Declaration of Confor	UK	Marine / Shi
Marine / Shipping	other		Environment	
* *	Confirmat	ion 🔊	Environmental Con-	



Further information

Subject to change without notice © Copyright Siemens Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus). Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2926-5AT61

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2926-5AT61

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT2926-5AT61

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT2926-5AT61&lang=en

last modified:

1/18/2021 🖸