

Product data sheet

Characteristics

LAD322

Power splitter box, TeSys Deca Fram 2,63A, for 2 starters composed by GV2ME**3/LS1D323 and LC1D**3 (spring terminal)



Main

Range of Product	TeSys fuse-disconnector
Device short name	LAD
Product or Component Type	Power splitter box
Product Compatibility	LAD32.
Poles description	3P

Complementary

Number of outgoers	2
[Ie] rated operational current	63 A
Net Weight	0.26 lb(US) (0.12 kg)



Ordering and shipping details

Category	US10I1222341
Discount Schedule	0I12
GTIN	3389110468076
Returnability	No
Country of origin	FR

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	1.26 in (3.2 cm)
Package 1 Width	3.62 in (9.2 cm)
Package 1 Length	2.87 in (7.3 cm)
Package 1 Weight	5.47 oz (155.0 g)
Unit Type of Package 2	S02
Number of Units in Package 2	30
Package 2 Height	5.91 in (15 cm)
Package 2 Width	11.81 in (30 cm)
Package 2 Length	15.75 in (40 cm)
Package 2 Weight	10.95 lb(US) (4.965 kg)

Offer Sustainability

REACH Regulation	 REACH Declaration
REACH free of SVHC	Yes
EU RoHS Directive	Compliant  EU RoHS Declaration
Toxic heavy metal free	Yes
Mercury free	Yes

China RoHS Regulation	 China RoHS Declaration
RoHS exemption information	 Yes
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

Contractual warranty

Warranty	18 months
----------	-----------