

Low PIM QD 4.3-10 Female to N Female Adapter



PE9148

RF Adapters Technical Data Sheet

Configuration

- QD 4.3-10 Female Connector 1
- N Female Connector 2
- 50 Ohm

Features

- Max VSWR of 1.25:1 up to 6 GHz
- PIM levels lower than -160 dBc

Applications

- Allows Connection Between Series
- General Purpose Test
- Low PIM Applications
- Mobile Communications Systems

- Low PIM Design
- Straight Body Geometry
- Silver Plated Beryllium Copper Contact
- Quick Disconnect (QD) on the 4.3-10 Interface
- Base Stations
- Distributed Antenna Systems
- (DAS)
- Small Cells

• Feeder Cables

Description

Pasternack's PE91482 QD 4.3-10 female to type N female adapter is part of our full line of RF components available for sameday shipping. Our 4.3-10 to type N adapter has a female to female gender configuration in a low PIM design. PE91482 4.3-10 female to type N female adapter operates to 6 GHz. The Pasternack RF adapter provides excellent VSWR of 1.25:1 maximum and passive intermodulation of -160 dBc maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/ disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Minimum	Typical	Maximum	Units
DC		6	GHz
		1.25:1	
		-160	dBc
5,000			MOhms
	DC	DC	DC 6 1.25:1 -160

Electrical Specification Notes: Values at 25° C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM QD 4.3-10 Female to N Female Adapter PE91482

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



Low PIM QD 4.3-10 Female to N Female Adapter



PE91482

RF Adapters Technical Data Sheet

Mechanical Specifications

Size

Description	Connector 1	Connector 2		
Туре	4.3-10 Female N Female			
Polarity	Standard Standard		Standard	Standard
Mating Cycles	500	500		

Material Specifications

	Connector 1		Connector 2		
Description	Material	Plating	Material	Plating	
Туре	QD 4.3-10 Female		N Female		
Contact	Beryllium Copper	Silver	Beryllium Copper	Silver	
Insulation	PTFE		PTFE		
Outer Conductor	Bronze	Tri-Metal	Bronze	Tri-Metal	
Body	Brass	Tri-Metal	Brass	Tri-Metal	

Environmental Specifications

Temperature

Operating Range

-55 to +120 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM QD 4.3-10 Female to N Female Adapter PE91482

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



Low PIM QD 4.3-10 Female to N Female Adapter



RF Adapters Technical Data Sheet

PE91482

Low PIM QD 4.3-10 Female to N Female Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: Low PIM QD 4.3-10 Female to N Female Adapter PE91482

URL: https://www.pasternack.com/4.3-10-female-n-female-straight-adapter-pe91482-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE91482 CAD Drawing Low PIM QD 4.3-10 Female to N Female Adapter

