

3.5mm Male to 1.85mm Female Adapter



RF Adapters Technical Data Sheet

PE9745

Configuration

- 3.5mm Male Connector 1
- 1.85mm Female Connector 2

- •50 Ohms
- Straight Body Geometry

Features

Max VSWR of 1.3:1 up to 34 GHz

• Gold Plated Beryllium Copper Contact

Applications

• Allows Connection Between Series

General Purpose Test

Description

Pasternack's PE9745 3.5mm male to 1.85mm female adapter is part of our full line of RF components available for same-day shipping. The 3.5mm connector mates mechanically with commercially available SMA and 2.92mm (K) connectors. The 1.85mm connector mates mechanically with commercially available 2.4mm connectors. Our 3.5mm to 1.85mm adapter has a male to female gender configuration. PE9745 3.5mm male to 1.85mm female adapter operates to 34 GHz. The Pasternack RF adapter provides good VSWR of 1.3:1 maximum.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Pasternack also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		34	GHz
VSWR			1.3:1	

Mechanical Specifications

Size

 Length
 0.863 in [21.92 mm]

 Width
 0.312 in [7.92 mm]

 Weight
 0.014 lbs [6.35 g]

Description	Connector 1	Connector 2	
Туре	3.5mm Male	1.85mm Female	
Polarity	Standard	Standard	

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 3.5mm Male to 1.85mm Female Adapter PE9745

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



3.5mm Male to 1.85mm Female Adapter



RF Adapters Technical Data Sheet

PE9745

Material Specifications

Connecto	Connector 1		Connector 2		
n Material	Plating	Material	Plating		
3.5mm Male		1.85mm Female			
Beryllium Copper	Gold	Beryllium Copper	Gold		
•		Passivated Stainless Steel			
Passivated Stainless Steel					
Passivated Stainless Steel					
	3.5mm Male Beryllium Copper Passivated Stainless Steel	n Material Plating 3.5mm Male Beryllium Copper Gold Passivated Stainless Steel	Material Plating Material 3.5mm Male 1.85mm Female Beryllium Copper Gold Beryllium Copper Passivated Stainless Steel		

Environmental Specifications

Temperature

Operating Range

-65 to +125 deg C

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

3.5mm Male to 1.85mm Female Adapter from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 3.5mm Male to 1.85mm Female Adapter PE9745

URL: https://www.pasternack.com/3.5mm-male-1.85mm-female-straight-adapter-pe9745-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE9745 CAD Drawing

3.5mm Male to 1.85mm Female Adapter

