



Part Number : 1301530144

Product Description : Safeway User
Attachable GFCI In-Line, Manual Reset, Non-Corded, 20A, 120V

Series Number : 130153

Status : Active

Product Category : Power Distribution

Engineering Number : 20054

Documents & Resources

Drawings

Drawing 1301530144_sd.pdf

Product Environment Compliance

Compliance

GADSL/IMDS	Not Relevant
China RoHS	Not Reviewed per SJ/T 11365-2006
EU ELV	Not Relevant
Low-Halogen Status	Not Reviewed per IEC 61249-2-21
REACH SVHC	Not Reviewed per D(2023)8585-DC (23 Jan 2024)
EU RoHS	Not Reviewed per EU 2015/863

Multiple Part Product Compliance Statements

- Eu RoHS
- REACH SVHC
- Low-Halogen

Multiple Part Industry Compliance Documents

- IPC 1752A Class C
- IPC 1752A Class D
- Molex Product Compliance Declaration
- IEC-62474
- chemSHERPA (xml)

EU RoHS Certificate of Compliance

Part Details

General

Status	Active
Category	Power Distribution
Series	130153
Description	Safeway User Attachable GFCI In-Line, Manual Reset, Non-Corded, 20A, 120V
Enclosure Rating	NEMA 4
NEMA Configuration	N/A
Product Family	Ground Fault Circuit Interrupter (GFCI) Products
Product Name	Safeway
Type	GFCI Commercial Duty, Single Phase
UPC	78678828436

Agency

CSA	LR6837
UL	E66308

Electrical

Current - Maximum per Contact	20.0A
GFCI	Yes-In-line
GFCI Reset	Manual
Ground Continuity Monitor	No
Open Neutral Relay	Yes
Voltage - Maximum	120V AC

Physical

Cord Diameter	N/A
Cord Grip Body Size	Internal Double C-Clamp
Cord Length	N/A
Cord Type	N/A
Feed-Thru	Yes
Flip Lid	No
Material - Housing	N/A
Mounting Style	Portable

Net Weight	249.475/g
Number of Receptacles	1
Packaging Type	Bag
Receptacle Type	N/A

This document was generated on Apr 15, 2024