

# Jumper Along 1x2 black 16A



Part number	09 33 000 9852
Specification	Jumper Along 1x2 black 16A
HARTING eCatalogue	https://b2b.harting.com/09330009852

Image is for illustration purposes only. Please refer to product description.

#### Identification

Category	Accessories
Series	Han <sup>®</sup> ES Press
Type of accessory	Plug-in jumper
Description of the accessory	1x 2 Longitudinal

#### Version

Details When using plug-in jumpers within Han <sup>®</sup> ES Press must be used.	hoods of high construction
---	----------------------------

## **Technical characteristics**

Rated current	16 A
Rated voltage	500 V
Rated impulse voltage	6 kV
Pollution degree	3
Rated voltage acc. to UL	600 V
Insulation resistance	>10 <sup>10</sup> Ω
Contact resistance	≤1 mΩ
Limiting temperature	-40 +125 °C
Mating cycles	≥5
Material properties	
Material (contacts)	Copper alloy

Page 1 / 2 | Creation date 2024-01-25 | Please note that the data specified here were taken as extracts from the online catalogue. Please refer to the user documentation for the complete and up-to-date information and data. Please also note that the user is responsible for validating functionality, conformity with applicable laws and directives, as well as for the electrical safety in the particular application. HARTING Electric Stiftung & Co. KG | Wilhelm-Harting-Straße 1 | 32339 Espelkamp | Germany Phone +49 5772 47-97100 | electric@HARTING.com | www.HARTING.com Product data sheet 09 33 000 9852 Jumper Along 1x2 black 16A



### Material properties

Surface (contacts)	Tin plated
Material (accessories)	Polyamide (PA)
Colour (accessories)	RAL 5004 (black blue)
Material flammability class acc. to UL 94	V-0
RoHS	compliant
ELV status	compliant
China RoHS	e
REACH Annex XVII substances	Not contained
REACH ANNEX XIV substances	Not contained
REACH SVHC substances	Not contained
Commercial data	
Packaging size	5
Net weight	1.7 g
Country of origin	China
European customs tariff number	85389099
GTIN	5713140192591
ETIM	EC002943
eCl@ss	27440292 Connector component (accessories)