## RMCN22BD

Harmony Analog, Isolated analog converter, 0...10 V or 4...20 mA to 0...10 V or 4...20 mA





### Main

Range of Product	Harmony Analog
Product or Component Type	Voltage/current converter
Analogue input type	Current 420 mA Voltage 010 V DC
Analogue output type	Current 420 mA <= 500 Ohm by cabling Voltage 010 V >= 100 kOhm by cabling

#### Complementary

Protection Type	Short-circuit protection on output Overvoltage protection on output (+/- 30 V) Reverse polarity protection on output
Abnormal analogue output voltage	-150 V no input or input wire broken
Abnormal analogue output current	430 mA no input or input wire broken
[Us] rated supply voltage	24 V DC +/- 20 %, non isolated
Current consumption	<= 40 mA voltage output <= 60 mA current output
Local signalling	For power ON LED (green)
Measurement error	+/- 10 % of full scale 20 °C electromagnetic interference of 10 V/m) +/- 1 % of full scale 20 °C
Repeat accuracy	+/- 0.2 % full scale 20 °C +/- 0.6 % full scale 60 °C
Temperature coefficient	200 ppm/°C
Clamping connection capacity	1 x 2.5 mm² 2 x 1.5 mm²
Tightening torque	5.319.74 lbf.in (0.61.1 N.m)
Marking	CE
Surge withstand	0.5 kV 1.2/50 μs IEC 61000-4-5
[Ui] rated insulation voltage	2 kV
Fixing mode	By screws mounting plate) Clip-on 35 mm symmetrical DIN rail)
Safety reliability data	MTTFd = 73.2 years B10d = 67582
Net Weight	0.26 lb(US) (0.12 kg)

### Environment

Standards	IEC 60584-1	
	IEC 60947-1	
Product Certifications	GL	
	CSA	
	UL	
IP degree of protection	IP20 terminal block)	
	IP50 housing)	
Fire resistance	1562 °F (850 °C) IEC 60695-2-1	
	1562 °F (850 °C) UL	
Shock resistance	50 gn 11 ms IEC 60068-2-27	

Vibration resistance	5 gn 10100 Hz)IEC 60068-2-6	
Resistance to electrostatic discharge	6 KV in contact)IEC 61000-4-2 level 3 8 kV in air)IEC 61000-4-2 level 3	
Resistance to fast transients	1 KV IEC 61000-4-4 on input-output) 2 kV IEC 61000-4-4 on power supply)	
Disturbance radiated/conducted	CISPR 22 group 1 - class B CISPR 11	
Ambient Air Temperature for Storage	-40185 °F (-4085 °C)	
Ambient Air Temperature for Operation	32122 °F (050 °C) mounting side by side 32140 °F (060 °C) 2 cm spacing	
Pollution degree	2 IEC 60664-1	

2 1	AND THE PERSON MODILIE (ADA DO)
Category	22375 - INTERFACE MODULE(ABA,R,S)
Discount Schedule	CP2
GTIN	3389110108903
Nbr. of units in pkg.	1
Package weight(Lbs)	3.63 oz (103 g)
Returnability	No
Country of origin	ID

### **Packing Units**

Unit Type of Package 1	PCE	
Package 1 Height	1.06 in (2.7 cm)	
Package 1 width	3.23 in (8.2 cm)	
Package 1 Length	3.35 in (8.5 cm)	

## Offer Sustainability

Sustainable offer status	Green Premium product	
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov	
REACh Regulation	REACh Declaration	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)	
Mercury free	Yes	
RoHS exemption information	€Yes	
China RoHS Regulation	☑ China RoHS Declaration	
Environmental Disclosure	Product Environmental Profile	
Circularity Profile	☑ End Of Life Information	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.	

#### Contractual warranty


Contractual warranty	
Warranty	18 months

# Product data sheet Dimensions Drawings

# RMCN22BD

### Analog Interface (Converter)

### Dimensions




(1) Terminal block AB1TP435U or AB1RRNTP435U2

# Product data sheet Mounting and Clearance


# RMCN22BD

### Mounting

## Mounting on Rails AM1 \*\*\*\*\*



### **Panel Mounting**




## RMCN22BD


### Analog Interface: Voltage/Current Converter

### Wiring Diagrams

### Current input signal



### Voltage input signal



The input, output and power supply lines must be kept away from the power cables to avoid effects due to induced interference.

The input and output cables must be shielded as indicated in the schemes and must be kept away from each other.